

NOVENTA 3.5 SURFACE - NV3.5SM

Installation Guide



NOTICE:

For proper installation, have a qualified electrician install this product. Before installation of any luminary onto an electrical junction box, be sure to disconnect power. This luminary must be wired and grounded in accordance with the National Electrical Code, local codes, and ordinances. Wire supply connections must be made with U.L. or ETL approved connectors. Check that luminary voltage and building voltage are the same.

CAUTION:

EXERCISE SPECIAL CARE AND SAFETY WHILE INSTALLING AND SERVICING LUMINARY. USE OF SOFT GLOVES AND PADDED MATERIALS ARE RECOMMENDED DURING HANDLING TO AVOID MARRING THE FINISH.

INSTRUCTION:

1. TURN OFF POWER at fuse box before proceeding.
2. If joining multiple fixtures together, remove LENS and REFLECTOR and loosen the set screws on JOINER BRACKETS. Connect wires between fixtures using connectors provided (if needed) and push excess wire into fixtures. DO NOT PINCH WIRES BETWEEN THE PARTS. Join sections together and secure joined fixtures with the JOINER BRACKET set screws. (Maintenance note: Removing the LENS and REFLECTOR will allow access to ballasts/drivers.)
3. Bring conduit to 1/2" CONDUIT ENTRY on fixture from building structure and attach building power using U.L. approved wire connectors: Connect neutral (white) to the the supply neutral, connect the line wire (black) to the supply line wire. Fasten ground wire(s) (green) to ground wire. Push excess wires into the fixture.
4. Install mounting screws into MOUNTING HOLES. Mounting screws must support 50lbs. Use blocking as needed. Verify fixture orientation, i.e., NV3.5WI (indirect) or NV3.5WD (direct).
5. Install REFLECTOR and LENS.
6. Turn on power.

